

Using the Detachable Keyboard with the Tablet

1



Rotate the center docking port so that it is facing up. Unfold/ lift up the metal stand from the back of the main Keyboard, and place on a flat surface such as a lap, table, or desk.

2



Install the Tablet directly onto the Keyboard docking port, making sure to align the port connectors. The Keyboard and Tablet will automatically function together.

Note:
Battery or external power supply is not required to use the Keyboard.

3



Fold the Keyboard toward the Tablet for portability and as a protective cover to shield the screen.

Specifications

| | |
|---------------------------|--|
| Compatible Models | DT301, DT311, DT313 series Tablets |
| Interface | 54-pin docking connector |
| Keys | QWERTY, full row of F1 to F12 function keys Keys for Windows shortcuts, media controls, screen brightness |
| Touchpad | Supports multi-touch |
| Material | ABS with aluminum alloy |
| Water and Dust Resistance | IP42 |
| Dimensions (H x W x D) | 0.55in x 11.5in x 8.53in/ 14mm x 291.8mm x 216.7mm |
| Weight | 1.55lbs/ 700g |
| Regulatory | FCC Class B, CE, RoHS compliant |
| Temperature | Operation: 5°C – 50°C; Storage: -20°C – 65°C |
| Humidity | 10% – 85% non-condensing |

Detachable Keyboard

BASIC OPERATION GUIDE

ENGLISH



INTRODUCTION

Thank you for acquiring the Detachable Keyboard for use with DT Research Rugged Tablets. Designed to be easily connected without switching and pairing, this Detachable Keyboard is ideal for your 2-in-1 applications. When folded while attached to the DT Research tablet, the Detachable Keyboard also serves as a protective cover to shield the screen. The flexible 2-in-1 design of the Detachable Keyboard and the tablet provides users both a laptop and tablet experience with multiple applications.

Package Contents

- 1. One DT Research Detachable Keyboard
- 2. Basic Operation Guide

The Detachable Keyboard

